

TECHNICAL DATA

Fluke BK120 SmartTrace™ Breaker Finder and 107 Pocket Digital Multimeter





Key features

- Locates the correct breaker quickly and accurately
- Advanced NCV Mode to indicate proximity and detection of voltage on sockets/outlets, supply cords, or terminal strips
- GFCI outlets—with an integrated GFCI test, you can feel secure knowing that your GFCI equipped outlets are functioning properly
- Current and voltage measurements
- Measures resistance and continuity to check for broken wires

Product overview: Fluke BK120 SmartTrace™ Breaker Finder and 107 Pocket Digital Multimeter

Presenting the perfect pair of tools for both seasoned electrical professionals and DIY enthusiasts - The BK120 with 107 DMM

The Fluke BK120 with NCV mode

This versatile device simplifies electrical tasks, circuit tracing, and troubleshooting for electricians, homeowners, and maintenance professionals. The BK120 features a Breaker Finder and Transmitter, ensuring accurate circuit breaker identification, eliminating uncertainty, and ultimately saving valuable time. It's suitable for use in CAT III 150 V environments and boasts a comfortable and ergonomic design.

Key Features:

- Dual Sensitivity: Detects AC voltage in low and high voltage situations, enhancing safety
- Built-in GFCI Tester
- Bright flashlight
- Low battery indicator
- Auto sleep mode

Fluke 107 Pocket Digital Multimeter

The Fluke 107 is a compact, rugged digital multimeter that fits in your pocket. It's ideal for quick troubleshooting, offering reliable measurements for AC/DC voltage, current, resistance, capacitance, diode, frequency, and duty-cycle. With a CAT III 600V safety rating, it ensures your safety on the job.

Key Features:

- AC and DC voltage
- AC and DC current
- Resistance
- Capacitance
- Diode
- Frequency and duty-cycle

Specifications: Fluke BK120 SmartTrace™ Breaker Finder and 107 Pocket Digital Multimeter

Fluke BK120 SmartTraceu2122 Breaker Finder

	BK120 Transmter	BK120 Receiver
Safety rating	CAT III 150 V	CAT III 150 V
Rated operating voltage	110 V AC to 125 V AC at 6 mA	u2014
Rated frequency	50/60 Hz	u2014
GFCI test	u2713	u2014
Wiring check	u2713	u2014
Wiring indication	1 red, 2 green	u2014
Breaker finder indication	u2014	Visual and audio
NCV detection	u2014	90 V AC to 240 V AC, 50/60 Hz ttDual sensitivity ttVisual and audio indications
Flashlight	u2014	u2713
Auto power off	u2014	u2713
Low baery indication	u2014	u2713
Power supply	Line powered	2 AAA

Fluke 107 Pocket Digital Multimeter

Accuracy is available for one year after calibration, operating from 18 u00b0C to 28 u00b0C and relative humidity from 0% to 75%. The format of the accuracy specification is: u00b1 ([% of reading] + [least significant digit])

Precision specifications			
	Range	Resolution	Accuracy
AC voltage tt(40 Hz to 500 Hz) ¹	6.000 V tt60.00 V tt600.0 V	0.001 V tt0.01 V tt0.1 V	1.0 % + 3
DC voltage	6.000 V tt60.00 V tt600.0 V	0.001 V tt0.01 V tt0.1 V	0.5 % + 3
Exchange millivolts	600.0 mV	0.1 mV	3.0 % + 3
Diode test²	2.000 V	0.001 V	10 %
Resistance tt(ohm)	400.0 u03a9 tt4.000 ku03a9 tt40.00 ku03a9 tt400.0 ku03a9 tt4.000 Mu03a9 tt40.00 Mu03a9	0.1 u03a9 tt0.001 ku03a9 tt0.01 ku03a9 tt0.1 ku03a9 tt0.001 Mu03a9 tt0.01 Mu03a9	0.5 % + 3 tt0.5 % + 2 tt0.5 % + 2 tt0.5 % + 2 tt0.5 % + 2 tt1.5 % + 3
Capacitor³	50.00 nF tt500.0 nF tt5.000 u03bcF tt50.00 u03bcF tt500.0 u03bcF tt1000 u03bcF	0.01 nF tt0.1 nF tt0.001 u03bcF tt0.01 u03bcF tt0.1 u03bcF tt1 u03bcF	2 % + 5 tt2 % + 5 tt5 % + 5 tt5 % + 5 tt5 % + 5 tt5 % + 5

Frequency ⁴ Hz tt(10 Hz u2013 100 kHz)	50.00 Hz tt500.0 Hz tt5.000 kHz tt50.00 kHz tt100.0 kHz	0.01 Hz tt0.1 Hz tt0.001 kHz tt0.01 kHz tt0.1 kHz	0.1 % + 3	
Duty cycle ⁴	1 % to 99 %	0.10 %	1 % typical case ⁵	
AC current tt(40 Hz - 200 Hz)	4.000 A tt10.00 A	0.001 A tt0.01 A	1.5 % + 3	
DC	4.000 A tt10.00 A	0.001 A tt0.01 A	1.5 % + 3	
tt ttt 1. All AC current, frequency, and duty cycle are specified from 1% to 100% of the range. Input values below 1% of range are not specified. ttt 2. Typically, the open circuit test voltage is 2.0 V and the short circuit current is < 0.6 mA. ttt 3. The parameters do not include errors due to test lead capacitance and capacitor substrate (up to 1.5 nF in the 50 nF range). ttt 4. All AC current, frequency, and duty cycle are specified from 1% to 100% of the range. Input values below 1% of range are not specified. ttt 5. Typically, the frequency is 50 Hz or 60 Hz and the duty cycle is 10% to 90%. tt tt				
Features	Overload protection	Input impedance (nominal value)	Common mode rejection ratio	Normal mode rejection ratio
AC voltage	600 V ¹	>10 Mu03a9 <100 pF ²	>60 dB at 50 Hz or 60 Hz at DC current	u2212
Exchange millivolts	600 mV	>1M, <100 pF	>80 dB at 50 Hz or 60 Hz	u2212
DC voltage	600 V ¹	>10 Mu03a9 <100 pF	>100 dB at 50 Hz or 60 Hz at DC current	>60 dB at 50 Hz or 60 Hz
tt ttt 1. Up to 6 x 105 V Hz ttt 2. For medium voltage (alteating current), the input impedance is approximately 1 Mu03a9. tt tt				
General technical indicators				
The highest voltage applied to any terminal and ground		600 V		
Display (LCD)		6000 counts, updated three times per second		
Type of baery		Two AAA baeries (NEDA 24A, IEC LR03)		
Baery life		At least 200 hours		
Temperature				
Operating temperature		0 u00b0C to 40 u00b0C		

Storage temperature	-30 u00b0C to 60 u00b0C
Relative humidity	
Working humidity	No condensation below 10 u00b0C ttu2264 90 % at 10 u00b0C to 30 u00b0C; u2264 75 % at 30 u00b0C to 40 u00b0C
Working humidity, 40 Mu03a9 range	u2264 80 % at 10 u00b0C to 30 u00b0C; u2264 70 % at 30 u00b0C to 40 u00b0C
Altitude	
Working elevation	2000 m
Storage altitude	12,000 m
Temperature coefficient	0.1 X (specified accuracy) / u00b0C (<18 u00b0C or >28 u00b0C)
Current input fuse protection	11A, 1000V fast-melting type, must use Fluke designated parts
Volume (height x width x length)	142 mm x 69 mm x 28 mm
Weight	200 g
Protection level	IEC 60529: IP 40
Safety	IEC 61010-1: 600 V CAT III, pollution degree 2
Electromagnetic environment	IEC 61326-1: Portable
Electromagnetic compatibility	Applicable only in Korea. Class A equipment (industrial broadcasting and communication equipment) ¹
¹ This product meets the requirements of industrial (Class A) electromagnetic wave equipment, which should be noted by the seller or user. The device is suitable for use in a work environment, not a home environment.	

Ordering information



Fluke BK120/107 Kit

Fluke BK120 SmartTrace™ Breaker Finder and 107 Pocket Digital Multimeter

Includes:

- BK120
 - Breaker Finder Receiver
 - Transmitter
 - Batteries
 - Quick Reference guide
- 107 Pocket Digital Multimeter
 - Fluke 107 palm-sized digital multimeter
 - (1 pair) TL75 Hard Point™ Test Leads
 - (2) AAA batteries (installed)
 - SmartStrap™ intelligent magnetic, multi-purpose lanyard
 - 1-year warranty

Optional accessories

Description

Fluke C115 Soft Carrying Case

Includes two padded pockets for protection of two test tools, such as a digital multimeter and 60 Series IR thermometer and a pouch for test leads and other accessories.

The Fluke logo consists of the word "FLUKE" in a bold, black, sans-serif font, followed by a registered trademark symbol (®). It is set against a solid yellow rectangular background.

Fluke. *Keeping your world up and running.®*

©2024 Fluke Corporation.
Specifications subject to change without notice.
10/2024

**Modification of this document is not permitted
without written permission from Fluke Corporation.**