

TECHNICAL DATA

# Fluke BK120 SmartTrace™ Breaker Finder with NCV mode



**FLUKE®**





## Key features

- Locates the correct breaker quickly and accurately
- Advanced NCV mode enables the detection of AC voltage on supply cords or terminal strips, indicating proximity and actual voltage presence in both low and high voltage situations
- GFCI outlets—with an integrated GFCI test, you can feel secure knowing that your GFCI equipped outlets are functioning properly

## Product overview: Fluke BK120 SmartTrace™ Breaker Finder with NCV mode

### Easy to use and accurate

The BK120 is a tool for identifying circuit breakers and detecting voltage in electrical panels. This must-have device is perfect for electricians, homeowners, and maintenance professionals who want to simplify their electrical work and troubleshooting. The BK120 has two main components:

- the Breaker Finder and
- the Transmitter.

With BK120, you can work more safely and efficiently, saving time by accurately identifying circuit breakers without guesswork. The BK120 is suitable for CAT III 150 V environments, making it versatile for residential and commercial applications with a compact and ergonomic design to ensure comfortable handling during prolonged use.

### Dual-sensitivity

- Indicates proximity and actual detection of AC voltage on supply cords or terminal strips with advanced NCV mode, catering to both low and high voltage situations.

### One-button GFCI tests

- The one-button GFCI tests consist of a transmitter connected to the electrical outlet or fixture, allowing you to test the operation of GFCI outlets.

### Audible and Visual Alerts

- The Breaker Finder offers both audible alerts and visual cues to signal the presence of AC electric fields and identify the correct breaker.

## Specifications: Fluke BK120 SmartTrace™ Breaker Finder with NCV mode

	BK120 Transmier	BK120 Receiver
Safety rating	CAT III 150 V	CAT III 150 V
Rated operating voltage	110 V AC to 125 V AC at 6 mA	u2014
Rated frequency	50/60 Hz	u2014
GFCI test	u2713	u2014
Wiring check	u2713	u2014
Wiring indication	1 red, 2 green	u2014

Breaker finder indication	u2014	Visual and audio
NCV detection	u2014	90 V AC to 240 V AC, 50/60 Hz ttDual sensitivity ttVisual and audio indications
Flashlight	u2014	u2713
Auto power off	u2014	u2713
Low battery indication	u2014	u2713
Power supply	Line powered	2 AAA

## Ordering information



### Fluke BK120

Fluke BK120 SmartTrace™ Breaker Finder

Includes:

- Breaker Finder Receiver
- Transmitter
- Batteries
- Quick Reference Guide

### Optional accessories Description

**Fluke C50 Meter Case** Carry your 11X series digital multimeter on your belt

**FLUKE®**

**Fluke.** *Keeping your world up and running.®*

©2024 Fluke Corporation.  
Specifications subject to change without notice.  
10/2024

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**