User Manual

TRIPLETT

UA100A
Universal Power Adaptor
With 1USB&1Type-C

PRODUCT OVERVIEW

1. Multi-socket
2. USA/AU/UK/EU Plugs
3. LED Indicator
   LED solid:
   Power on
   LED slow red light:
   1. Possible overload (trying to reset, if still stand, please indicator again)
   2. Fuse burn out, please check or change
4. USB-A Port
5. USB-C Port

SPECIFICATIONS

- Model: UA100A
- Rating: 100-250V~10A Max,2500W Max
- Input: 100-250V~,50-60Hz,0.5A
- USB Output: 5.0V⎓2.1A(Total),2.1A Max Per Port
- Total DC Output: 10.5W
- Dimensions: 85mm x 55mm x 50mm
- Operating Temperature: 0°C ~ 40°C

APPLICABLE OUTLETS

1. Adapter can accept Type A, B, C, D,E, F, G, I,O plugs.

2. Adapter can plug into Type A,B,C,D,E,F,G,H,I,J,K,L,M,N and O outlets.



2-POLE UNEARTHED DEVICES

The product is suitable for use with most electronic devices up to 2500W at 250V and 1000W at 100V.It can be used with a multitude of appliances such as:Laptops,Small travel hair dryers,Travel irons,Electric fan,Table lamp, Electric razors,etc.

Please check the safety data sheet or data plate on the device to find this information before plugging it in.

USB DEVICES

Camera,Smartphone,Tablet,Portable Game Console, Bluetooth speaker, Power bank,etc.

HOW TO USE THE ADAPTER

Features:

Built-in multi-nation plugs can be selected to fit all outlets in different countries. Safety function switch ensure only one plug energized.

Attentions:

1. Please make sure that the button is reset when the button is pushed out and retracted to the bottom, and if the button is not reset, it means that the pug has not been pushed in place and will affect the normal use.
2. Only one plug-type can be used at one time by sliding the knob selection, other plug-pins are locked automatically.

USA

Slightly press the button and slide to the down for USA plug completely as shown.make sure the contact blades are turned to the parallel position.

Recover the plug: press and hold the "USA" button to release and continue to pull up, until the plug completely pull the top and then release the button, then the button will reset and lock the plug.

Australia / NZ

Slightly press the button and slide to the down for AUS plug completely as shown .make sure the contact blades are turned to the parallel position.

Recover the plug: press and hold the "AUST" button to release and continue to pull up, until the plug completely pull the top and then release the button, then the button will reset and lock the plug.

United Kingdom

Slightly press the button and slide to the down for UK plug completely as shown .Pull out the insulated ground pin from the housing.

Recover the plug: press and hold the "UK" button to release and continue to pull up, until the plug completely pull the top and then release the button, then the button will reset and lock the plug.

EUROPE

Slightly press the button and slide to the down for EUROPE plug completely as shown .make sure the contact blades are turned to the parallel position.

Recover the plug: press and hold the "EUROPE" button to release and continue to pull up, until the plug completely pull the top and then release the button, then the button will reset and lock the plug.

REPLACEMENT OF THE FUSE



1. Take out ❶
2. You also could change new fuse.
   standard: 240Vac 10A, 6.3*25.4mm,BS1362 approved.

Notes:

1.You should remove all the device before you change the new fuse.
2.Please confirm whether there are water flowed out from the access equipment in the power rating.
3.Please confirm whether the product is wet and there is water flowed out.

CAUTION

- Always disconnect Adapter from the outlet when not in use.
- Before use,please read this instruction carefully! This product does not convert voltage(AC-AC), in order to avoid possible damage to your device or other safety hazards,please make sure the power outlet you intend to use has the proper voltage to run your device before using this adapter.
- Indoor use only.
- Misuse can lead to electrical shock.
- The length of the USB cable should be less than 3M.
- The travel adaptor is for temporary use only and that it shall not be used permanently.
- Against inserting an adaptor into another adaptor shall be provided by the manufacturer.
- No grounding,This product is for use with unearthed or double insulated appliances only.

COMPATIBLE COUNTRIES

EU PLUG:

A: Albania, Algeria, Angola, Argentina, Austria, Azores
B: Balearic Islands, Bangladesh, Belgium, Bolivia, Bosnia, Brazil, Bulgaria, Burkina Faso, Burundi
C: Cameroon, Canary Island, Cape Verde, Central African Republic, Channel Islands, Chile, Comoros, Congo, Croatia, Cote d' Ivoire, Cyprus
D: Denmark, Djibouti
E: Egypt, El Salvador, Equatorial Guinea, Eritrea, Faeroe Islands, Finland, France
G: Gabon, Germay, Gibraltar, Greece, Greenland, Guadeloupe, Guinea, Guinea-Bissau
H: Hungary
I: Iceland, India, Indonesia, Iran, Iraq, Israel, Italy
K: Kazakhstan, Korea, Kuwait
L: Laos, Lebanon, Lithuania, Luxembourg
M: Macedonia, Madagascar, Malaiia, Mali, Martinique, Mauritania, Mauritius, Morocco, Mozambique, Myanmar
N: Nepal, Netherlands, Niger, Norway
O: Oman
P: Pakistan, Paraguay, Peru, Philippines, Poland, Portugal
R: Romania, Russia, Rwanda
S: Senegal, Somalia, Spain, Sudan, Suriname, Sweden, Switzerland, Syria
T: Thailand, Togo, Tunisia, Turkey
U: Uruguay
V: Vietnam
Z: Zambia

AUS PLUG:

A: American Samoa, Argentina, Australia
C: China
E: El Salvador
F: Fiji
G: Guatemala
K: Kiribati
N: Nauru, New Zealand
P: Panama, Papua New Guinea
S: St. Vincent
T: Tajikistan, Tonga
U: Uruguay

USA PLUG:

A: American Samoa, Anguilla, Antilles, Aruba
B: Bahamas, Bangladesh, Barbados, Bermuda, Bolivia, Brazil
C: Cambodia, Canada, Cayman Islands, China, Colombia, Costa Rica, Cuba
E: Ecuador, El Salvador
G: Guam, Guatemala
H: Guyana, Haiti, Honduras
J: Japan, Jamaica
L: Laos, Liberia
M: Maldives, Mexico, Micronesia, Montserrat
N: Netherlands, Nicaragua, Niger
O: Okinawa
P: Panama, Peru, Philippines, Puerto Rico
S: St. Vincent, Saudi Arabia
T: Tahiti, Taiwan, Thailand, United States
V: Venezuela, Vietnam, Virgin Islands(US&British)
Y: Yemen

UK PLUG:

B: Bahrain, Bangladesh, Belize, Botswana, Brunei
C: Cameroon, Channel Islands, Cyprus
D: Dominica
E: El Salvador
G: Gambia, Ghana, Gibraltar, Grenada, Guatemala, Guyana
H: Hong Kong, Iraq, Ireland, Isle of Man
J: Jordan, Kuwait
L: Lebanon
M: Macau, Malawi, Malaysia, Maldives, Malta, Mauritius, Myanmar
N: Nigeria
O: Oman
Q: Qatar
S: St. Lucia, St. Vincent, Saudi Arabia, Seychelles, Sierra Leone, Singapore
T: Tanzania
U: Uganda, United Arab Emirates, United Kingdom
V: Vietnam
Y: Yemen
Z: Zambia, Zimbabwe

Waste electrical products should not be disposed of with household waste.
Please recycle where facilities exist.
Check with your Local Authority for recycling advice.

660AC说明书	
品号	
日期	2024-01-25
版本	V1.0
制图	
审核	
核准	

Find Quality Products Online at: www.GlobalTestSupply.com sales@GlobalTestSupply.com