

BBT858L Pocket Digital Multimeter

Digital multimeter also measures temperature on its easy to read backlit display

Features:

- Designed for use by electricians, technicians, and serviceman who require an instrument that is accurate, reliable, and always ready for use
- Use on a broad variety of equipment including electronic and electrical components, devices, fuses, alarms and circuit boards
- 21 ranges including ohms, amps, AC/DC Volts and temperature
- A temperature probe is included for heating/cooling (HVAC) technicians
- 3 ½ digit, 1999 count backlit display
- Perfect for both electronic and electrical use
- Data hold freezes the reading on the display
- Soft silicone probes for safety and reliability
- Removable protective boot with rear stand
- CATII 600V rating
- Includes test leads, alligator clips, temperature probe and 9V battery
- 1 year warranty



Specifications

	Range
Basic Accuracy	±0.8%
AC Voltage	100mV to 600V
DC Voltage	0.1mV to 600V
DC Current	1μA to 10A
Resistance	0.1Ω to 2MΩ
Temperature	32 to 1300°F
Transistor hFE	0 to 1000 (NPN or PNP)
Continuity buzzer	Yes
Safety Category	CAT II-600V
Dimensions	3 x 5.75 x 1.75" (76.2 x 146 x 44.5mm)
Weight	6 oz. (170g)



Includes K-type temperature thermocouple

Ordering Information:

BBT858L Pocket Digital Multimeter

**CAT II
600V**

